



SD2000A– Integrated TFT LCD Display Controller

The SmartASIC **SD2000A** is a highly integrated TFT LCD controller chip with the latest SmartASIC advanced image-processing technology and an integrated ADC/PLL to form up an ultra low cost solution supporting analog input. The SD2000A has advanced programmable non-linear parametric cubic based scaling engine with proprietary sharpness adjustment and text enhancement. The SD2000A has robust handling of a wide variety of TFT LCD panels and strong support of standard or non-standard input timings.

FEATURES

- ◆ Integrated high speed triple 8-bit ADC/PLL support up to 100MHz for XGA-75Hz
- ◆ Advanced image processing with proprietary non linear parametric cubic based scaling engine
- ◆ Robust auto configuration for input mode detection and clock frequency and phase recovery for standard or non-standard input timing
- ◆ Support programmable Gamma Correction

Integrated ADC/PLL

- ⇒ Integrated triple 8-bit ADC and video capture PLL support up to 100MHz
- ⇒ Support 32-step fine phase adjustment for every resolution up to XGA
- ⇒ Integrated output PLL to generate output clock

Proprietary scaling engine and output processing

- ⇒ Programmable non-linear parametric cubic based scaling engine can be optimized for any expansion ratio
- ⇒ Independent expansion ratio in both horizontal and vertical direction
- ⇒ User programmable sharpness adjustment
- ⇒ Output digital brightness, contrast and color temperature adjustment with independent DSP
- ⇒ Triple 8-bit Gamma table dedicated to RGB gamma correction independently

Auto Configuration

- ⇒ Robust mode detection for standard or non-standard input timing
- ⇒ Accurate clock frequency and phase recovery

True color support for 6 bit panel

- ⇒ Proprietary spatial based dithering
- ⇒ Optional temporal based dithering

Support multiple TFT LCD panels

- ⇒ Programmable output timing parameters to match specifications of various TFT LCD panels
- ⇒ Single or dual pixel output (24/48 bit RGB)
- ⇒ Support power On/Off sequence to protect TFT LCD panel

Low-cost system solution

- ⇒ No external frame buffer required
- ⇒ 2-wire serial interface for CPU
- ⇒ 208 Pin PQFP Package
- ⇒ 2.5V power with 3.3V tolerant I/O
- ⇒ Power Management

Family members

- ⇒ SD2000A: support analog interface only, no Digital RGB input port, no T-CON (PQFP208 package)
- ⇒ SD2000: support analog and digital RGB input ports, but no T-CON (LBGA256 package)
- ⇒ SD2000AT: support analog input port and T-CON embedded, but no Digital RGB Input port (LBGA256 package)
- ⇒ SD2000T: support both analog and digital RGB input ports as well as T-CON embedded (LBGA 256 package)